



# 15 VOLT REDUCER AUTOTRANSFORMERS

DESIGNED AND MADE IN THE USA

OVER 40 YEARS AS THE INDUSTRY LEADER

- U.L. LISTED COMPONENTS
- FULLY RATED AT 50 OR 60 Hz

- CLEARLY MARKED ELECTRICAL RATINGS
- BLUE BAKED ENAMEL FINISH


REDUCER AUTOTRANSFORMERS

REDUCE 130 / 115 VOLTS → 115 / 100 VOLTS

REDUCE 15 VOLTS 300 → 1800 VA

IN STOCK

CATALOG NUMBER	MAX.VA (WATTS)	NOMINAL AMPS	WEIGHT LBS.	DIMENSIONS		
				H	W	D
1RT-22 G	300	3	2 1/2	2 1/2	3	3 5/8
1RT-30 G	400	4	3	2 1/2	3	3 7/8
1RT-45 G	550	5.5	3 3/4	2 1/2	3	4 3/8
1RT-65 G	750	7.5	4 1/2	3 1/2	3 3/4	4 1/4
1RT-85 G	1000	10	6	3 1/2	3 3/4	4 3/4
1RT-120 G	1400	14	8	3 1/2	3 3/4	5 1/2
1RT-150 G	1800	18	9 3/4	3 1/2	3 3/4	6



TYPICAL APPLICATIONS:

foreign 100V appliances to be used in the U.S.A.;

115V appliances to be used in countries with 127V supply;

avoid overheating 115V 60Hz FHP motors on 115V 50Hz by reducing voltage to 100V

- 6 FOOT POWER CORD WITH U.S. 3 PRONG PLUG
- BUILT-IN U.S. 3 WIRE GROUNDING RECEPTACLE

NOTE: WHEN USING A TRANSFORMER WITH MORE THAN ONE APPLIANCE AT A TIME, THE TOTAL WATTAGE OF ALL APPLIANCES USED TOGETHER SHOULD NOT EXCEED THE MAX.VA (WATTS) OF THAT TRANSFORMER.

QUALITY ENGINEERED

**TODD SYSTEMS**

INC.

PRECISION BUILT

FAX: (914) 963-3506

50 ASH STREET, YONKERS, NY, 10701 U.S.A.  
www.toddsystems.com

(914) 963-3400